

Link do produktu: <https://www.sklep.caraudioteam.pl/rockford-fosgate-t400-4-p-3752.html>



Rockford Fosgate T400-4

Cena	2 149,00 zł
Dostępność	Na zamówienie
Czas wysyłki	10 dni
Producent	Rockford Fosgate

Opis produktu



**CEA-2006
Compliant:**
**Number of
Channels:** 4

Rated Power 60 Watts x 4 @
(RMS Continuous 4-Ohm
Power): 100 Watts x 4 @
2-Ohm

200 Watts x 2 @
4-Ohm Bridged
2-Ohm x 2
Bridged Stable

Total Power 400 Watts RMS
(Sum of Rated
Power):

Dynamic Power *Front Channels*
90 Watts x 2 @
4-Ohms 0° Res
(PVC/PowerCube®
Measurement): 154 Watts x 2 @
2-Ohms 0° Res

Rear Channels
90 Watts x 2 @
4-Ohms 0° Res
154 Watts x 2 @
2-Ohms 0° Res

Bridgeable: Yes

Frequency Response: 20Hz to 20kHz
+/- 1dB

Efficiency (average): 69% @ 4-Ohm
68% @ 2-Ohm

Total Harmonic Distortion *4-Ohm: <1.0%*
2-Ohm: <1.0%
(THD+Noise):

Crossover Controls: Front High-Pass
(HP): 50-500Hz

24dB/octave
Butterworth
Front Low-Pass
(LP): 50-500Hz
24dB/octave
Butterworth
Rear High-Pass
(HP): 50-500Hz
24dB/octave
Butterworth
Rear Low-Pass
(LP): 50-500Hz
24dB/octave
Butterworth

Tone Controls:	<i>Front Channels -</i>
	<i>Punch EQ</i>
	Treble: 0dB to +12dB @ 12kHz
	Bass: 0dB to +18dB @ 45Hz
	<i>Rear Channels -</i>
	<i>Punch EQ</i>
	Treble: 0dB to +12dB @ 12kHz
	Bass: 0dB to +18dB @ 45Hz

Input Sensitivity: 150 mV to 4 V

Signal Input:	Front Low level: 1
	RCA pair
	Rear Low level:
	1 RCA pair

Signal Output: n/a

Power Input Connector:	Block
-------------------------------	-------

Power Wire Gauge:	8 AWG to 4 AWG
--------------------------	----------------

Speaker Output Connector:	Screw terminal barrier strip
----------------------------------	------------------------------

Speaker Wire Gauge:	8 AWG to 18 AWG
----------------------------	-----------------

Heat Sink Type:	Cast aluminum
------------------------	---------------

Cooling:	Convection
-----------------	------------

Remote Controls:	Optional Remote Punch EQ (overrides rear channel built-in Punch EQ)
-------------------------	--

Visual Indicators:	Power Thermal Protect
---------------------------	-----------------------------

Circuit Topology	Class-A/B
-------------------------	-----------

Class:

Operating Voltage: 9 - 16 VDC

Recommended Fuse 60 A
(not included)‡

Max. Current Draw (13.8V Sinewave)‡ 60 A

Average Current Draw (13.8V Music)‡ 30 A

Suggested Alternator: 75 A

Shipping Weight: 11.90 Lbs. (5.39 Kg.)

Dimensions (HxWxL): 2.14 x 8.14 x 13.66 (in)
5.42 x 20.68 x 34.69 (cm)

Dimensional Diagram:

The T400-4 amplifier is perfect for front/rear fading stereo systems or when dedicated amplification is required between front stage speakers and rear subwoofer(s). Thanks to the Dynamic Thermal Management, the small chassis design insures it can be installed in any location – like under front seats.

The Power T400-4 is a 4-channel amplifier capable of producing 100 Watts into each of its four channels at 2-Ohms. The T400-4 can run a 4-way full-range system or use component speakers on the front with subwoofers on the rear.

- 24dB/octave crossover
- 2/4 channel input switch
- MOSFET power supply
- MOSFET output stage
- 4 Gauge power/ground connectors
- Audiophile grade speaker connections