Dane aktualne na dzień: 29-03-2024 13:36

Link do produktu: https://www.sklep.caraudioteam.pl/jl-audio-hd6004-hd600-hd-6004-hd-600-4-p-3203.html



JL AUDIO HD600/4 HD600 HD 600/4 HD 600 4

Cena	**6 299,00 zł**
Dostępność	**Na zamówienie**
Czas wysyłki	**5 dni**
Producent	**JL AUDIO**

Opis produktu



Rated Continuous (RMS) Power @ 14.4 V

@ 4 Ω	150 W RMS x 4
@ 3 Ω	150 W RMS x 4
@ 2 Ω	150 W RMS x 4
@ 1.5 Ω	150 W RMS x 4
Bridged @ 8 Ω	300 W RMS x 2
Bridged @ 4 Ω	300 W RMS x 2

Rated Continuous (RMS) Power @ 12.5 V

@ 4 Ω	150 W RMS x 4
@ 3 Ω	150 W RMS x 4
@ 2 Ω	150 W RMS x 4
@ 1.5 Ω	150 W RMS x 4
Bridged @ 8 Ω	300 W RMS x 2
Bridged @ 4 Ω	300 W RMS x 2

General Specifications

Frequency Response	6 Hz - 30 kHz (+0, -1dB)
S/N Ratio, referred to highest rated power	>110 dB (A-weighted, 20 Hz - 20 kHz noise bandwidth)

S/N Ratio, referred to 1 W	>88.2 dB (A-weighted, 20 Hz - 20 kHz noise bandwidth)
Damping Factor @ 4 Ω	>300 / 50 Hz
Damping Factor @ 2 Ω	>150 / 50 Hz
THD+N @ Rated Power	<0.03% @ 4 Ω per Ch.
Input Voltage Range @ RCA Inputs	Switchable from 200 mV - 2 V RMS to 800 mV - 8 V RMS
Min Copper Power / Ground Wire Gauge	4 AWG wire
Fuse Rating	50 A (AFS, AGU or MaxiFuse™)

Signal Processing

Filter Modes	Low-Pass or High-Pass
Filter Slope (dB/Octave)	12dB or 24 dB
Filter Frequency Range	50-500 Hz
Detented, Calibrated Filter Freq. Potentiometers	Yes
Filter Defeatable?	Yes
Remote Level Control	Optional (HD-RLC)
Remote Level Modes	2 or All Channels
Channel Input Mode Switch	Yes (2/4 ch.)
Pass-Through Preamp Output Type	Buffered
Source Channel Selection for PreOuts	Yes

Physical Specifications

Height (H)	1.93 in / 49 mm
Width (W)	10.74 in / 273 mm
Depth (D)	8.29 in / 211 mm