

Link do produktu: <https://www.sklep.caraudioteam.pl/jl-audio-xd8008v2-xd800-8v2-xd-800-8v2-p-3201.html>



JL AUDIO XD800/8v2 XD800 8v2 XD 800 8v2

Cena	5 499,00 zł
Dostępność	Dostępny
Producent	JL AUDIO

Opis produktu



[Rated Continuous \(RMS\) Power @ 14.4 V](#)

@ 4 Ω	75 W RMS x 8
@ 2 Ω	100 W RMS x 8
Bridged @ 4Ω	200 W RMS x 4

[Rated Continuous \(RMS\) Power @ 12.5 V](#)

@ 4 Ω	60 W RMS x 8
@ 2 Ω	90 W RMS x 8
Bridged @ 4Ω	180 W RMS x 4

[General Specifications](#)

Frequency Response	12 Hz - 22 kHz (+0, -1dB)
S/N Ratio, referred to highest rated power	>104 dB below rated power (A-weighted, 20 Hz - 20 kHz noise bandwidth)
S/N Ratio, referred to 1 W	>84 dB (A-weighted, 20 Hz - 20 kHz noise bandwidth)
Damping Factor @ 4 Ω	>150 / 50 Hz
Damping Factor @ 2 Ω	>75 / 50 Hz
THD+N @ Rated Power	<1% @ 2 Ω per Ch.
Input Voltage Range @ RCA Inputs	Switchable from 200 mV - 2 V RMS (Low) to 800 mV - 8 V RMS (High)
Min Copper Power / Ground Wire Gauge	4 AWG wire
Fuse Rating	80 A (AFS, AGU or MaxiFuse™)

Signal Processing

Filter Modes	Low-Pass or High-Pass
Filter Slope (dB/Octave)	12dB
Filter Frequency Range	50-500 Hz
Detented, Calibrated Filter Freq. Potentiometers	Yes
Filter Defeatable?	Yes
Remote Level Control	Optional (HD-RLC)
Remote Level Modes	2 or 4 or All Channels
Channel Input Mode Switch	Yes (2/4/6/8 ch.)
Pass-Through Preamp Output Type	None
Source Channel Selection for PreOuts	N/A

Physical Specifications

Height (H)	2.05 in / 52 mm
Width (W)	14.73 in / 374 mm
Depth (D)	7.09 in / 180 mm