

Dane aktualne na dzień: 29-04-2024 03:00

Link do produktu: <https://www.sklep.caraudioteam.pl/rockford-fosgate-p300x2-p-3721.html>



Rockford Fosgate P300X2

Cena	1 450,00 zł
Dostępność	Na zamówienie
Producent	Rockford Fosgate

Opis produktu



CEA-2006
Compliant:

Number of
Channels: 2

Rated Power 100 Watts x 2 @

(RMS Continuous Power):	4-Ohm 150 Watts x 2 @ 2-Ohm 300 Watts x 1 @ 4-Ohm Bridged
--------------------------------	---

Total Power 300 Watts
(Sum of Rated Power):

Dynamic Power (PVC/PowerCube® Measurement):	120 Watts x 2 @ 4-Ohms 0° Res 203 Watts x 2 @ 2-Ohms 0° Res
---	--

Bridgeable: Yes

Frequency Response:	20Hz-20kHz
----------------------------	------------

Efficiency (average): 69% @ 4-Ohm

Total Harmonic Distortion (THD+Noise):	4-Ohm: <1.0% 2-Ohm: <1.0%
--	------------------------------

Crossover Controls: High-Pass: 50Hz -
250Hz @
12dB/Octave
Butterworth

Low-Pass: 50Hz
- 250Hz @
12dB/Octave
Butterworth
All-Pass: Yes

Tone Controls: 0dB to +14dB @
12.5kHz
0dB to +18dB @
45Hz

Input Sensitivity: 150 mV - 12 V

Signal Input: *Hi/Low Level: 1*
RCA Pair

Signal Output: *Low Level: 1 RCA*
Pair

Power Input Connector: Captive C-Clamp

Power Wire Gauge: 8 AWG to 4 AWG

Speaker Output Connector: Captive C-Clamp

Speaker Wire Gauge: 8 AWG to 18 AWG

Heat Sink Type: Die Cast Aluminum

Cooling: Convection

Remote Controls: Optional Punch Level Control (PLC2) Ready

Visual Indicators: Power/Protect/Thermal LED
Input Clip LED
Output Clip LED

Circuit Topology Class: Class-A/B

Operating Voltage: 9 - 16 VDC

Recommended Fuse 50 A
(not included):

Max. Current Draw 45 A
(13.8V Sinewave):

Average Current Draw (13.8V Music):	23 A
--	------

Suggested Alternator:	75 A
------------------------------	------

Shipping Weight:	9.5 Lbs. (4.3 Kg.)
-------------------------	--------------------

Dimensions (HxWxL):	2.38 x 7.76 x 9.86 (in) 6.05 x 19.71 x 25.04 (cm)
----------------------------	--

Dimensional Diagram:	
-----------------------------	--

Clipping Calibrated Level Eliminates Audible Noise

CLEAN to nowa zintegrowana technologia Rockforda sygnalizowana jest za pomocą diody i służy do ustawienia czułości wzmacniacza do sygnału wejściowego w celu zapobieżenia przed uszkodzeniem głośników. System wychwytuje przesterowania wejściowe i wyjściowe pozwalając na precyzyjne ustawienie czułości, co zapobiega uszkodzeniu głośników i daje czysty precyzyjny sygnał dźwiękowy. W komplecie dołączona płyta do ustawienia CLEAN.