

Dane aktualne na dzień: 07-05-2024 10:09

Link do produktu: <https://www.sklep.caraudioteam.pl/rockford-fosgate-t600-4-p-3753.html>



Rockford Fosgate T600-4

Cena	2 850,00 zł
Dostępność	Na zamówienie
Producent	Rockford Fosgate

Opis produktu



CEA-2006
Compliant:

Number of
Channels: 4

Rated Power 100 Watts x 4 @

(RMS Continuous Power):	4-Ohm 150 Watts x 4 @ 2-Ohm 300 Watts x 2 @ 4-Ohm Bridged 2-Ohm x 2 Bridged Stable
--------------------------------	--


Total Power 600 Watts RMS
(Sum of Rated Power):

Dynamic Power	<i>Front Channels</i> 139 Watts x 2 @ 4-Ohms 0° Res
(PVC/PowerCube® Measurement):	236 Watts x 2 @ 2-Ohms 0° Res
	<i>Rear Channels</i> 140 Watts x 2 @ 4-Ohms 0° Res 236 Watts x 2 @ 2-Ohms 0° Res

Bridgeable: Yes

Frequency Response:	20Hz to 20kHz +/- 1dB
----------------------------	--------------------------

Efficiency (average): 70% @ 4-Ohm
64% @ 2-Ohm



Total Harmonic Distortion (THD+Noise):	4-Ohm: <1.0% 2-Ohm: <1.0%
--	------------------------------

Crossover Controls:	Front High-Pass (HP): 50-500Hz 24dB/octave Butterworth Front Low-Pass (LP): 50-500Hz 24dB/octave Butterworth Rear High-Pass (HP): 50-500Hz 24dB/octave Butterworth Rear Low-Pass (LP): 50-500Hz 24dB/octave Butterworth
----------------------------	--

Tone Controls:	<i>Front Channels - Punch EQ</i> Treble: 0dB to +12dB @ 12kHz Bass: 0dB to +18dB @ 45Hz <i>Rear Channels - Punch EQ</i> Treble: 0dB to +12dB @ 12kHz Bass: 0dB to +18dB @ 45Hz
-----------------------	---

Input Sensitivity: 150 mV to 4 V

Signal Input: Front Low level: 1 RCA pair
Rear Low level: 1 RCA pair

Signal Output: Low Level: 1 RCA pair

Power Input Connector: Block

Power Wire Gauge: 4 AWG

Speaker Output Connector: Screw terminal barrier strip

Speaker Wire Gauge: 8 AWG to 18 AWG

Heat Sink Type: Cast aluminum

Cooling: Convection

Remote Controls:	Optional Remote Punch EQ (overrides rear channel built-in Punch EQ)
-------------------------	--

Visual Indicators:	Power Thermal Protect
---------------------------	-----------------------------

Circuit Topology Class:	Class-A/B
--------------------------------	-----------

Operating Voltage:	9 - 16 VDC
---------------------------	------------

Recommended Fuse (not included):	80 A
--	------

Max. Current Draw (13.8V Sinewave):	80 A
--	------

Average Current Draw (13.8V Music):	40 A
--	------

Suggested Alternator:	75 A
------------------------------	------

Shipping Weight:	12.00 Lbs. (5.44 Kg.)
-------------------------	-----------------------

Dimensions (HxWxL):	2.14 x 8.14 x 14.91 (in) 5.42 x 20.68 x 37.86 (cm)
----------------------------	---

Dimensional Diagram:

Wzmocniacz czterokanałowy z serii Power ■

The T600-4 amplifier offers the perfect balance of power output and compact design required for high performance audio systems. The 4-channel configuration allows fine tuning adjustments between front stage component systems and rear surround speakers. The built-in crossover also allows the rear channels to be configured for running one or two subwoofers

The Power T600-4 is a 4-channel amplifier capable of producing 150 Watts into each of its four channels at 2-Ohms. The T600-4 can run a 4-way full-range system or use component speakers on the front with subwoofers on the rear.

- 24dB/octave crossover
- 2/4 channel input switch
- MOSFET power supply
- MOSFET output stage
- 4 Gauge power/ground connectors
- Audiophile grade speaker connections
- RCA pass-thru outputs