

Link do produktu: <https://www.sklep.caraudioteam.pl/jl-audio-6w2v3-4-6w3v3-6w3v3-4-p-3169.html>



JL AUDIO 6W2v3-4 6W3v3 6W3v3-4

Cena	1 599,00 zł
Dostępność	Na zamówienie
Czas wysyłki	5 dni
Producent	JL AUDIO

Opis produktu



General Specifications

Continuous Power Handling (RMS)	150 W
Recommended RMS Amplifier Power	50 - 150 W
Nominal Impedance (Znom)	4 Ω

Physical Specifications

Nominal Diameter	6.5 in / 165 mm
Overall Diameter (A)	6.85 in / 174 mm

Mounting Hole Diameter (B)	5.5 in / 140 mm
Bolt Hole Circle (C)	6.125 in / 156 mm
Magnet Diameter (D)	4.25 in / 108 mm
Mounting Depth (E)	4.25 in / 108 mm
Driver Displacement	0.02 cu ft / 0.57 L
Net Weight	6.1 lb / 2.8 kg

[Parameters](#)

Free Air Resonance (Fs)	41.80 Hz
Electrical "Q" (Qes)	0.533
Mechanical "Q" (Qms)	11.027
Total Speaker "Q" (Qts)	0.508
Equivalent Compliance (Vas)	0.181 cu ft / 5.13 L
One-Way Linear Excursion (Xmax)*	0.35 in / 8.89 mm
Reference Efficiency (no)	0.0700%
Efficiency (1 W / 1 m)**	80.49 dB SPL
Effective Piston Area (Sd)	17.36 sq in / 0.0112 sq m
DC Resistance (Re)	3.476 Ω